

CW500/8

5" LF Driver



MOUNTING INFORMATION

Overall Diameter	130 mm
Bolt Circle Diameter	138 mm
Baffle cutout Diameter	115 mm
Depth	55 mm
Mounting Depth	49 mm
Net Weight	0,6 Kg

SPECIFICATIONS

Nominal Impedance	8 Ohm
Power	80W
Sensitivity (1W/1m)	92 dB
Frequency Range	80-6000 Hz
Voice Coil Diameter	25 mm
Magnet	Ferrite
Magnet weight	10 oz
Basket Material	Steel

THIELE AND SMALL PARAMETERS

Qes	1,816
Qms	4,500
Qts	1,194
Vas	3,791 l
Sd	86,54 cm ²
Mms	6,990 gr
Bl	4,131 Tm
Mmd	6,527 gr
Cms	356,508 μm/N