

CW400/4

4" LF driver



MOUNTING INFORMATION

Overall Diameter	105 mm
Bolt Circle Diameter	114 mm
Baffle cutout Diameter	127 mm
Depth	52 mm
Mounting Depth	48 mm
Net Weight	0.35 Kg

SPECIFICATIONS

Nominal Impedance	4 Ohm
Power	30 W
Sensitivity (1W/1m)	89 dB
Frequency Range	100-6000 Hz
Voice Coil Diameter	20 mm
Magnet	Ferrite
Magnet weight	8 oz
Basket Material	Steel

THIELE AND SMALL PARAMETERS

Qes	3,240
Qms	5,574
Qts	2,049
Vas	0,887 l
Sd	54,07 cm ²
Mms	5,517 gr
Bl	3,265 Tm
Mmd	5,288 gr
Cms	213,766 μm/N