

CW501/4

5" LF Driver



MOUNTING INFORMATION

Overall Diameter	127 mm
Bolt Circle Diameter	139 mm
Baffle cutout Diameter	112 mm
Depth	55 mm
Mounting Depth	50 mm
Net Weight	0.6 Kg

SPECIFICATIONS

Nominal Impedance	4 Ohm
Power	40W
Sensitivity (1W/1m)	92 dB
Frequency Range	80-6000 Hz
Voice Coil Diameter	25 mm
Magnet	Ferrite
Magnet weight	10 oz
Basket Material	Steel

THIELE AND SMALL PARAMETERS

Qes	1,556
Qms	4,540
Qts	1,159
Vas	2,583 l
Sd	89,88 cm ²
Mms	7,649 gr
Bl	3,672 Tm
Cms	225,149 μm/N